



2 Station Kiosk Cabinet



Parts list

Ikea:

- 1 "Akurum" base cabinet, 12"W x 30H x 24"D, nexus birch veneer (approx \$40)
- 2 Nexus 12x30 birch doors (one is just used as back panel (\$19ea)
- 2 Integral door hinges for one door (\$10)
- 1 pkg 4 NUMERAR legs, 4" (\$14)
- 2 VIKA BYSKE table tops, white, 55"x27" (square one end and rounded on other. each one cut down to form a back to back "L") (\$70ea.)

Other supplies:

- 2 Legs 3" diameter x 34 " long, satin chrome, part # CAM-620-8S-ST from Outwater Hardware, Lincoln Park, NJ (\$67 ea.)

<http://www.outwaterhardware.com/catalog/form08.asp?page=445>

$\frac{3}{4}$ " plywood, approx 10"x22" to attach the underside of the two "L" countertops. Exact size should be determined in field to fit into opening of cabinet base.

- 3 - 3" "L" brackets and wood screws to attach countertop to inside of base cabinet

- 2 - 2" wire grommets, available locally or from Outwater

<http://www.outwaterhardware.com/catalog/form08.asp?page=263>

Note: the base cabinet was not designed to be free standing; it was to be connected to other similar cabinets and/or to a wall. To improve its stability, I have added 8 wood triangle braces glued and screwed in place on each inside corner of base cabinet.

Once assembled data port holes should be drilled through the counter tops and base shelves for power and network cabling.

More detailed photos available.

Contact: sid@motonet.com